



Specification document of S-58LM20A

Component manufacturer	ABLIC
Model number	S-58LM20A
Datasheets	S-58LM20A Series TEMPERATURE SENSOR IC (ablic.com)
Specification Ver	01.00.00 Sep 12,2022 New release
Documentation provided	Rui Long Lab Inc. https://rui-long-lab.com/

1. Component Software IF specification	2
2. File Structure and Definitions	4

License

Open Source Software for Embedded Components ("OSS-EC") is open source software files and related documentation files for component products used in computer systems and other applications. OSS-EC is provided to those who accept the OSS-EC Terms of Use for the OSS-EC site; see https://oss-ec.com/license_agreement/ for the OSS-EC Terms of Use. By downloading the OSS-EC from the OSS-EC site or obtaining the OSS-EC by any means, you accept the Terms of Use. Please read and accept the Terms of Use before using the OSS-EC. If you do not agree to the Terms of Use, please do not use the OSS-EC. We reserve the right to change these Terms of Use at any time and for any reason. We strongly recommend that you review the Terms of Use periodically.

1. Component Software IF specification

The software interface specifications based on the S-58LM20A component specifications are as follows.

The voltage value-to-physical value conversion equation is a linear conversion equation as shown in the equation below.

ADC value to voltage value conversion formula


$$v_i = (a_i \times i_{ADC_vdd}) / 2^{i_{ADC_bit}} \quad [V]$$

Voltage value to physical value conversion formula

$$y = (v_i - i_{S58LM20A_xoff}) / i_{S58LM20A_gain} + i_{S58LM20A_yoff} \quad [^{\circ}C]$$

$$i_{S58LM20A_min} \leq y \leq i_{S58LM20A_max}$$

a_i	A/D conversion value	
v_i	Sensor output voltage value [V]	
i_{ADC_vdd}	Sensor supply voltage value [V]	
i_{ADC_bit}	A/D conversion bit length	
y	Temperature value [$^{\circ}C$]	
#define $i_{S58LM20A_xoff}$	(<u>0.561111F</u> * i_{ADC_vdd})	// X offset [V]
#define $i_{S58LM20A_yoff}$	<u>30.0F</u>	// Y offset [$^{\circ}C$]
#define $i_{S58LM20A_gain}$	(<u>-0.00436F</u> * i_{ADC_vdd})	// Gain [V/ $^{\circ}C$]
#define $i_{S58LM20A_max}$	<u>130.0F</u>	// Temperature Max [$^{\circ}C$]
#define $i_{S58LM20A_min}$	<u>-30.0F</u>	// Temperature Min [$^{\circ}C$]



2. File Structure and Definitions

S58LM20A.h

```
#include "user_define.h"

// Components number
#define iS58LM20A          103U          // NXP S58LM20A

// S58LM20A System Parts definitions
#define iS58LM20A_xoff      ( 0.561111F*iADC_vdd ) // X offset [V]
#define iS58LM20A_yoff      30.0F                // Y offset [°C]
#define iS58LM20A_gain      ( -0.00436F*iADC_vdd ) // Gain [V/°C]
#define iS58LM20A_max        130.0F                // Temperature Max [°C]
#define iS58LM20A_min        -30.0F                // Temperature Min [°C]

extern const tbl_adc_t tbl_S58LM20A;
```

S58LM20A.cpp

```
#include      "S58LM20A.h"

#if      iS58LM20A_ma == iSMA                                // Simple moving average filter
static float32 S58LM20A_sma_buf[iS58LM20A_SMA_num];
static const sma_f32_t S58LM20A_Phy_SMA =
{
    iInitial ,                                // Initial state
    iS58LM20A_SMA_num ,                       // Simple moving average number & buf size
    0U ,                                       // buffer position
    0.0F ,                                    // sum
    &S58LM20A_sma_buf[0]                      // buffer
};

#elif      iS58LM20A_ma == iEMA                                // Exponential moving average filter
static const ema_f32_t S58LM20A_Phy_EMA =
{
    iInitial ,                                // Initial state
    0.0F ,                                    // Xn-1
    iS58LM20A_EMA_K                           // Exponential smoothing factor
};

#elif      iS58LM20A_ma == iWMA                                // Weighted moving average filter
static float32 S58LM20A_wma_buf[iS58LM20A_WMA_num];
static const wma_f32_t S58LM20A_Phy_WMA =
{
    iInitial ,                                // Initial state
    iS58LM20A_WMA_num ,                       // Weighted moving average number & buf size
    0U ,                                       // buffer poition
    iS58LM20A_WMA_num * (iS58LM20A_WMA_num + 1)/2 , // kn sum
    &S58LM20A_wma_buf[0]                      // Xn buffer
};

#else                                           // Non-moving average filter
#endif

#define iDummy_adr      0xffffffff            // Dummy address

const tbl_adc_t tbl_S58LM20A =
{
```

```

        iS58LM20A          ,
        iS58LM20A_pin      ,
        iS58LM20A_xoff     ,
        iS58LM20A_yoff     ,
        iS58LM20A_gain     ,
        iS58LM20A_max      ,
        iS58LM20A_min      ,
        iS58LM20A_ma       ,

    #if    iS58LM20A_ma == iSMA          // Simple moving average filter
        &S58LM20A_Phy_SMA      ,
        (ema_f32_t*) iDummy_adr ,
        (wma_f32_t*) iDummy_adr

    #elif  iS58LM20A_ma == iEMA          // Exponential moving average filter
        (sma_f32_t*) iDummy_adr ,
        &S58LM20A_Phy_EMA      ,
        (wma_f32_t*) iDummy_adr

    #elif  iS58LM20A_ma == iWMA          // Weighted moving average filter
        (sma_f32_t*) iDummy_adr ,
        (ema_f32_t*) iDummy_adr ,
        &S58LM20A_Phy_WMA

    #else          // Non-moving average filter
        (sma_f32_t*) iDummy_adr ,
        (ema_f32_t*) iDummy_adr ,
        (wma_f32_t*) iDummy_adr

    #endif

};

```